

# Smart Web Manager for AP-ACS500 Door Access Control System

The screenshot shows the web interface for the AddPac Door Access Control System. The header includes the title "Door Access Control System" and "Version 1.0.0". A notification banner states "Access control setting changed" with a link to "To apply setting, click here to transmitting to terminal." The user is logged in as "Administrator". The main menu includes "Home", "User and Terminal", "Access Control", "Card", and "Log and Report". The main content area features a welcome message and four functional buttons: "Import User and Terminal", "Terminal Sync.", "Register a Card", and "Event Log". Each button has an icon and a brief description of its function.

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

**Welcome to AddPac Technology Door Access Control System.**

The door access control system(DACS) interworks with AddPac IP-Next system to manage the door access and access control related configuration. You may execute applicable features through each menu below and detail configuration can be accessible from each menu in upper menu.

- Import User and Terminal**  
Import user and terminal list from IP-Next system to use for Door Access Control System (DACS).
- Terminal Sync.**  
Synchronize user, access group and schedule policy with specified terminal(s).
- Register a Card**  
Register a new card to access terminal.
- Event Log**  
Search event log who accessed terminal and what system logged with various search condition.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

**AddPac**

**AddPac Technology**

2012, Sales and Marketing

# Contents

- DACS Login
- DACS Main
- User List
- Terminal List
- Import User and Terminal
- Terminal Sync
- Access Control Group
- Schedule Template
- Day Template
- Card List
- Register a Card
- Event Log

# DACS Login

**DACS Login**  
Execute ACS1000 to enter IP address, then DACS accessible log in screen will be opened.



**Administrator Authentication**  
Enter administrator ID and password.  
Click on log in button. Authentication will be completed.

# DACS Main

The screenshot shows the DACS Main interface. At the top, the title "Door Access Control System" is displayed with "Version 1.0.0" below it. A notification banner reads "Access control setting changed" with a sub-message "To apply setting, click here to transmitting to terminal." and a "Help | Logout" link. The user is identified as "Administrator". A navigation menu includes "Home", "User and Terminal", "Access Control", "Card", and "Log and Report". Below the menu, a main heading reads "Technology Door Access Control System." followed by a paragraph: "system(DACS) interworks with AddPac IP-Next system to manage the door access and access control related configuration. You may es through each menu below and detail configuration can be accessible from each menu in upper menu." The main content area features four shortcut cards: "Import User and Terminal" (with a person and terminal icon), "Terminal Sync." (with a terminal and sync arrow icon), "Register a Card" (with a "NEW" badge and card icon), and "Event Log" (with a document and magnifying glass icon). A footer contains the "AddPac" logo and "Copyright © AddPac 1999-2011 All Rights Reserved".

**Main Menu**  
User may setup user and terminal management, access control card policy of DACS (Door Access Control System) through "Main Menu".

**Shortcut**  
An icon for shortcut. (Import User and Terminal / Terminal Sync / Register a Card / Event Log)

# DACS Logout

The screenshot displays the DACS web interface. At the top, the header includes the title "Door Access Control System Version 1.0.0", a notification "Access control setting changed" with a link to "here", and user information "Administrator". A "Logout" link is visible in the top right corner, highlighted by a red dashed box. A mouse cursor is positioned over the "Logout" link. A blue arrow points from the "Logout" link to a yellow text box at the bottom right of the screenshot.

**Logout**  
User may use when closing the currently logged in session or to log in as other administrator.

# User List (1/3)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

User List

Terminal List

Welcome  
Import User and Terminal  
Terminal Sync.  
The door access control system can execute applicable features through...

**Import User and Terminal**

Import user and terminal list from IP-Next system to use Door Access Control System (DACS).

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

**User List**

Search registered access terminal user or search for all users. You can proceed add/change/delete through the screen.

Search List: All Users Input search word Search Import User

	Extension	Name	Department	Access Policy	Date Created	Modify	Delete
1	1000	Choi jinsuk	/SFloor/SM/	Access Allow	2011-07-22 15:50:01		
2	1008	Kwon hyojuun	/SFloor/SM/	Access Allow	2011-07-22 15:50:00		
3	1014	Oh hyoungsuk	/SFloor/Framework/	Access Allow	2011-07-22 15:50:01		
4	1015	Choi byunggu	/SFloor/Framework/	Access Allow	2011-07-22 15:50:01		
5	1016	Lee seonghyun	/SFloor/Framework/	Access Allow	2011-07-22 15:50:01		

Page 1 of 1 Total: 5

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# User List (2/3)

**Door Access Control System**  
Version 1.0.0

① Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### User List

Search registered access terminal user or search for all users. You can proceed add/change/delete through the screen.

Search List: **All Users** Input search word Search

Extension	Name	Department	Access Policy	Date Created	Modify	Delete
1 1000	Choi jinsuk	/5Floor/SM/	Access Allow	2011-07-22 15:50:01		
2 1008	Kwon hyojun	/5Floor/SM/	Access Allow	2011-07-22 15:50:00		
3 1014	Oh hyoungsuk	/5Floor/Framework/	Access Allow	2011-07-22 15:50:01		
4 1015	Choi byunggu	/5Floor/Framework/	Access Allow	2011-07-22 15:50:01		
5 1016	Lee seonghyun	/5Floor/Framework/	Access Allow	2011-07-22 15:50:01		

Import User

All Users  
Last Name  
First Name  
Department  
Extension  
All Users  
Deleted Users

**User List**  
It displays imported user information from AddPac IP-Next System.  
User may search as Last Name/ First Name/ Department/ Extension/ All Users/ Deleted Users. User register, change, delete is possible.

Total: 5

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# User List (3/3)

**Door Access Control System**  
Version 1.0.0  
Access control setting changed  
To apply setting, click here to transmitting to terminal.  
Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### User Information and Policy

#### 1. Profile

Extension Number: 1000 (4 digit Number)  
First Name: Jinsuk  
Last Name: Choi  
Position: Researcher  
Department: /SFloor/SM  
E-Mail:   
Home Phone:   
Mobile Phone:   
Card Serial Number:   
Register a Card  
Picture:

#### 2. Security Access Policy

If you allow this user to access, be sure the checkbox to enable.

Allow access

Select available access group for this user. You can choose one or more access groups.

Access group list		
Group Name	Schedule Policy	Description
3floor door	All Allow	

Applied access group list		
Group Name	Schedule Policy	Description
default group	All Allow	default access...
job policy	working day	job policy acce...

To apply this features, select 'Apply' or 'Cancel'

Apply Cancel

**Profile**  
It displays imported user information from AddPac IP-Next System. Profile information will not be edited. User may register RF card by clicking "Register a Card" button.

**Security Access Policy**  
User may setup the access terminal authority of user.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved



# Terminal List (1/2)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

User List  
Terminal List  
Import User and Terminal  
Terminal Sync

Welcome  
The door access control system can execute applicable features through...

**Import User and Terminal**

Import user and terminal list from IP-Next system to use Door Access Control System (DACS).

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

**Terminal List**  
Display the registered door phone lists imported from IP-Next PBX system.

Import Terminal

Terminal Name	Description	Status	Extension	IP Address	Model Name	Version	Date Created	Detail View
1 2floor door terminal	2Floor door ter...	Disconnected	1006	172.16.10.4	AP-VAC50		2011-07-29 17:08:50	
2 3floor door terminal	3Floor door ter...	Disconnected	1002	172.16.10.1	AP-VAC20	8.50.001	2011-07-22 15:50:01	
3 5floor door terminal	5Floor door ter...	Disconnected	1005	172.16.10.2	AP-VAC50		2011-07-29 17:08:50	
4 The main entrance d...	The main entran...	Disconnected	<span style="color: red;">! Required setting</span>	172.16.10.3	AP-VAC100		2011-07-29 17:08:50	

Page 1 of 1 Total: 4

AddPac Copyright © AddPac 1999-2011. All Rights Reserved

# Terminal List (2/2)

**Door Access Control System**  
Version 1.0.0

④ Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### Terminal List

Display the registered door phone lists imported from IP-Next PBX system.

Import Terminal

	Terminal Name	Description	Status	Extension	IP Address	Model Name	Version	Date Created	Detail View
1	2floor door terminal	2Floor door ter...	Disconnected	1006	172.16.10.4	AP-VAC50		2011-07-29 17:08:50	
2	3floor door terminal	3Floor door ter...	Disconnected	1002	172.16.10.1	AP-VAC20	8.50.001	2011-07-22 15:50:01	
3	5floor door terminal	5Floor door ter...	Disconnected	1005	172.16.10.2	AP-VAC50		2011-07-29 17:08:50	
4	The main entrance d...	The main entran...	Disconnected	<span style="color: red;">❗ Required setting</span>	172.16.10.3	AP-VAC100		2011-07-29 17:08:50	

**Smart Web Manager**

**System Information**

- HW Version: 1.0
- SW Version: 8.00.001
- DACS: (0)
- DACS Registration: Fail
- SP: 172.17.250.250(5000)

Information: AddPac Technology, Model: VAC20\_02, DACS: (0), DACS Registration: Fail, SP: 172.17.250.250(5000)

Description

Total: 4

©AddPac Technology, all rights reserved

**Terminal List**  
Display the list of access terminals which is imported from AddPac IP-Next System. Access terminal status is updated periodically. User may access directly into the access terminal using 'Detail View' button.

AddPac Copyright © AddPac 1999-2011. All Rights Reserved

# Import User and Terminal (1/2)

The screenshot shows the 'Door Access Control System' web interface. The top navigation bar includes 'Home', 'User and Terminal', 'Access Control', 'Card', and 'Log and Report'. A dropdown menu for 'User and Terminal' is open, showing options like 'User List', 'Terminal List', 'Import User and Terminal', and 'Terminal Sync'. A yellow starburst highlights the 'Import User and Terminal' option. A blue arrow points from this option to a larger, detailed view of the 'Import User and Terminal' page.

The detailed view shows the 'Import User and Terminal' page with the following sections:

- 1. User list to be imported**
  - Total Users: 12 Changed: 1 Added: 11 Deleted: 6
  - Display new added users of IP-Next PBX. The selected user will be imported to DACS(Door Access Control System).

Extension	Name	Department
<input checked="" type="checkbox"/>	1111	Hwang Wooseun /SFloor/
<input checked="" type="checkbox"/>	1005	Julian Jonathan /SFloor/
<input checked="" type="checkbox"/>	1013	Ramon Jorge /SFloor/
<input checked="" type="checkbox"/>	1260	White Nigel /SFloor/
<input checked="" type="checkbox"/>	1008	Kwon Hyogun /SFloor/SM/
<input checked="" type="checkbox"/>	1000	Choi jinsuk /SFloor/SM/
<input checked="" type="checkbox"/>	4099	Ham Siyoung /SFloor/SM/
- 2. Select Access Control Group Policy**
  - Select access control group policy for selected added users and you can select one or more groups.

Group Name	Description
<input type="checkbox"/>	3floor door
<input type="checkbox"/>	job policy
<input checked="" type="checkbox"/>	default group

Buttons for 'Apply' and 'Cancel' are visible at the bottom.

# Import User and Terminal (2/2)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Hide | Logout | Administrator

Home | User and Terminal | Access Control | Card | Log and Report

### Import User and Terminal

You can import the users and terminals from IP-Next PBX system.  
This job can be used when you first install or users and terminals are newly added or changed in a IP-Next PBX system.

User | Terminal

#### 1. User list to be imported

Total Users: 12 Changed: 1 Added: 11 Deleted: 6

Display new added users of IP-Next PBX.  
The selected user will be imported to DACS(Door Access Control System).

Extension	Name	Department
1111	Hwang Woodun	/3Floor/
1005	Julien Jonathan	/3Floor/
1013	Ramon Jorge	/3Floor/
1260	White Nigel	/3Floor/
1008	Kwon Hyolun	/3Floor/SM/
1000	Choi Ginsuk	/3Floor/SM/
4099	Ham Jiyoung	/3Floor/SM/

Display deleted users of IP-Next PBX.  
The selected user will be deleted from DACS(Door Access Control System).

Extension	Name	Department
1000	Choi Ginsuk	/3Floor/SM/
1015	Choi byunggu	/3Floor/Framework/
1016	Lee seonghyun	/3Floor/Framework/
1111	Hwang woodun	/3Floor/

#### 2. Select Access Control Group Policy

Select access control group policy for selected sticker users and you can select one or more groups.

Group Name	Description
3floor door	
job policy	job policy access group
<input checked="" type="checkbox"/> default group	default access group

To apply this features, select Apply or Cancel.

Apply | Cancel

AddPac Copyright © AddPac, 1999-2011. All Rights Reserved.

**User list to be imported**  
It performs to bring user lists to the access control system which is operated in AddPac IP-Next System. It displays a newly added/changed user information.

**Select Access Control Group Policy**  
Apply access authority policy regarding user (newly add/change) which is operated in AddPac IP-Next System.

# Terminal Sync (1/2)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home | User and Terminal | Access Control | Card | Log and Report

User List  
Terminal List  
Import User and Terminal  
Terminal Sync

Welcome  
The door access control system will execute applicable features this time.

**Terminal Sync.**  
Synchronize user, access group and schedule policy with selected terminals.  
Default checked terminals have updated configurations need to be synchronized.

<input checked="" type="checkbox"/>	Terminal Name	IP Address	Connection Status	Sync Status
<input checked="" type="checkbox"/>	2floor door terminal	172.16.10.4	Disconnected	Not yet synchronized
<input checked="" type="checkbox"/>	3floor door terminal	172.16.10.1	Disconnected	Not yet synchronized
<input checked="" type="checkbox"/>	5floor door terminal	172.16.10.2	Disconnected	Not yet synchronized
<input checked="" type="checkbox"/>	The main entrance door	172.16.10.3	Disconnected	Not yet synchronized

To synchronize with selected terminal above, select 'Sync' button below. Select 'Cancel' button to cancel.

Sync Cancel

AddPac Copyright © AddPac 1999-2011

# Terminal Sync (2/2)

**Door Access Control System**  
Version 1.0.0

① **Access control setting changed**  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### Terminal Sync.

Synchronize user, access group and schedule policy with selected terminals.  
Default checked terminals have updated configurations need to be synchronized.

<input checked="" type="checkbox"/>	Terminal Name	IP Address	Connection Status	Sync Status
<input checked="" type="checkbox"/>	2floor door terminal	172.16.10.4	Disconnected	Not yet synchronized
<input checked="" type="checkbox"/>	3floor door terminal	172.16.10.1	Disconnected	Not yet synchronized
<input checked="" type="checkbox"/>	5floor door terminal	172.16.10.2	Disconnected	Not yet synchronized
<input checked="" type="checkbox"/>	The main entrance door	172.16.10.3	Disconnected	Not yet synchronized

**Terminal Sync**  
Check the Sync status between access control system and access terminal. If the status is "Not yet synchronized", send access authority policy to the designated terminal with 'Sync' button.

select 'Cancel' button to cancel.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# Access Control Group (1/3)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

Welcome to AddPac Technology  
The door access control system (DACS) can execute applicable features through the system.

**Access Control Group**  
You can define a new Access Control Group with one or more terminals, users and schedule policy. Also, you can adjust priority of access control group using up/down arrow (or mouse drag/drop).

Add a Access Control Group

Group Name	Description	Schedule Policy	Date Created	Modify	Delete
3floor door		All Allow	2011-06-28 11:37:13		
job policy	job policy access group	working day	2011-07-04 17:06:47		
default group	default access group	All Allow	2011-06-28 11:37:13		

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# Access Control Group (2/3)

## Door Access Control System

Version 1.0.0

Access control setting changed

To apply setting, click [here](#) to transmitting to terminal.

Help | Logout

Administrator

Home
User and Terminal ▾
Access Control ▾
Card ▾
Log and Report ▾

### Access Control Group

You can define a new Access Control Group with one or more terminals, users and schedule policy. Also, you can adjust priority of access control group using up/down arrow (or mouse drag/drop).

Group Name	Description	Schedule Policy	Date Created	
↑↓ 3floor door		All Allow	2011-06-28 11:37:13	Modify <input type="checkbox"/> Delete <input type="checkbox"/>
↑↓ job policy	job policy access group	working day	2011-07-04 17:06:47	Modify <input type="checkbox"/> Delete <input type="checkbox"/>
↑↓ default group	default access group	All Allow	2011-06-28 11:37:13	Modify <input type="checkbox"/> Delete <input type="checkbox"/>

**Access Control Group**  
 Display newly created "Access Control Group" list.  
 User may search access authority policy or register by clicking 'Add a Access Control Group' button.  
 Priority of Access Group is adjustable using up/down arrow.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved



# Access Control Group (3/3)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Home | User and Terminal | Access Control | Card | Log and Report | Administrator

## Access Control Group

You can select terminals and schedule policy for this access control group. This access control group can be applied to one or more users at user setting page.

**1. Group Information**

Group Name\*

Description

**2. Select Terminal Access Policy**

Select terminal to apply this access control group.

Terminal List	
Terminal Name	Description
2floor door terminal	2Floor door terminal
3floor door terminal	3Floor door terminal

List of applied terminals	
Terminal Name	Description
5floor door terminal	5Floor door terminal
The main entrance...	The main entrance door

**3. Select Schedule Policy**

Select schedule template to apply this access control group.

All Allow

To apply this features, please select 'Add' or 'Apply' button. To cancel, Select 'Cancel' button.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

**Add a Access Control Group**  
Select Terminal Access Policy  
- Select access terminal to apply in access authority policy.  
Select Schedule Policy  
- Select schedule template to apply in access authority policy.

# Schedule Template (1/3)

The screenshot shows the 'Door Access Control System' web interface. The top navigation bar includes 'Home', 'User and Terminal', 'Access Control', 'Card', and 'Log and Report'. A red dashed box highlights the 'Access Control' menu, which is expanded to show 'Access Control Group', 'Schedule Template', and 'Day Template'. A blue arrow points from the 'Schedule Template' menu item to the 'Schedule Template' page below. The 'Schedule Template' page features a table with the following data:

	Template Name	Description	Date Created	Schedule Rules	Modify	Delete
1	All Allow	any time allowed	2011-07-28 16:28:46			
2	All Deny	any time denied	2011-07-28 16:29:09			
3	working day	working day template	2011-07-21 09:56:56			

The page also includes a 'Add a Schedule Template' button and a footer with 'AddPac Copyright © AddPac 1999-2011 All Rights Reserved'.

# Schedule Template (2/3)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### Schedule Template

Add schedule template for one or more schedule rules which define time, day and date duration. This schedule template can be applied to one or more access group policies.

Template Name	Description	Date Created	Schedule Rules	Modify	Delete
1 All Allow	any time allowed	2011-07-28 16:28:46			
2 All Deny	any time denied	2011-07-28 16:29:09			
3 working day	working day template	2011-07-21 09:56:56			

[Add a Schedule Template](#)

**Schedule Rules (All Allow)**

Name	Description	Start	End	Date	Day/Time	Access Policy	Date Created	Modify	Delete
All Allow		00:00	23:59	Sun, Mon, Tue, ...			2011-07-28 16:28:46		

**Schedule Template**

Change the Name of Schedule Template

Template Name : All Allow

Description : any time allowed

Apply Cancel

**Schedule Template**  
Display a newly created 'Schedule Template' list. Register/edit the schedule template by clicking 'Add a Schedule Template' button. User may apply various tools regarding newly created template.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# Schedule Template (3/3)

**Door Access Control System**  
Version 1.0.0

① Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### Schedule Rules (All Allow)

Display one or more schedule rules for a schedule template.  
Also, you can adjust priority of schedule rules using up/down arrow (or mouse drag/drop).

Name	Description	Start	End	Date	Day Template	Access Policy	Date Created	Modify	Delete
↑ All allow time	All allow time	00:00	23:59	Sun ,Mon ,Tue ,...		Allow	2011-07-21 09:59:15		

**Schedule Rule**  
You can define schedule rule which defines time duration to allow or deny the entrance.  
You can specify special day(s) with Day Template.

Rule Name\*

Description

Time  -

Day of Week  Mon  Tue  Wed  Thu  
 Fri  Sat  Sun

Day Template

Access Policy  Allow  Deny

To apply this feature, please select 'Add' or 'Apply' button. To cancel, Select 'Cancel' button.

**Schedule Rule**  
Display the list of newly created 'Schedule Rule'.  
User may register the rule to apply in schedule template by clicking 'Add a Schedule Rule' button. User may setup various options including (Time / Day of Week / Day Template / Access Policy ).

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# Day Template (1/2)

The screenshot shows the 'Door Access Control System' web interface. The top navigation bar includes 'Home', 'User and Terminal', 'Access Control', 'Card', and 'Log and Report'. A dropdown menu under 'Access Control' is open, showing 'Access Control Group', 'Schedule Template', and 'Day Template'. A yellow starburst icon is placed over the 'Day Template' option. A blue arrow points from this option to the 'Day Template' page.

The 'Day Template' page has a header with the system name and version (1.0.0), a notification for 'Access control setting changed', and the user 'Administrator'. Below the navigation bar, there is a section titled '12 Day Template' with a description: 'Add day template for one or more day rules which define special day(s). This template can be applied to one or more schedule rules.' A button 'Add a Day template' is located at the top right of the table area.

Template Name	Description	Date Created	Day(s)	Modify	Delete
1 Public Holidays	Public Holidays				
2 addpac holidays	addpac holidays				
3 test		2011-08-09 13:47:01			

At the bottom left of the page, there is a sidebar for 'Import User and Terminal' and a footer with 'AddPac Copyright © AddPac 1999-2011'.

# Day Template (2/2)

**Door Access Control System**  
Version 1.0.0

④ Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

## 12 Day Template

Add day template for one or more day rules which define special day(s).  
This template can be applied to one or more schedule rules.

Template Name	Description	Date Created	Day(s)	Modify	Delete
1 Public Holidays	Public Holidays				
2 addpac holidays	addpac holidays				
3 test		2011-08-09 13:47:01			

**Day List (Public Holidays)**

Name	Description	Start Day	End Day	Date Created	Modify	Delete
1 Independence Day	Independence Day	08-01	08-27			
2 Canada	Canada	07-01	08-31			

**Day Template**

Change the name of day template

Template Name : Public Holidays

Description : Public Holidays

Apply Cancel

**Day Template**  
Display newly created 'Day Template' list.  
After registering holiday or specific date by 'Add a Day Template' button, user may perform access authority policy by applying to 'Schedule Rule'.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# Card List (1/2)

The screenshot displays the 'Door Access Control System' web interface. The top navigation bar includes 'Home', 'User and Terminal', 'Access Control', 'Card', and 'Log and Report'. A notification banner at the top right states 'Access control setting changed' and provides a link to 'here' to transmit settings to the terminal. The user is logged in as 'Administrator'.

The main content area is titled 'Card List' and includes a search bar with a dropdown menu set to 'All card' and a 'Search' button. Below the search bar is a table of registered cards:

	Serial Number	Extension	Username	Status	Description	Date Created	Modify	Delete
1	4000238	1008	Kwon hyojun	<input checked="" type="checkbox"/> Specified	Temporary cards are issued.	2011-07-08 15:59:03		
2	123456789			<input type="checkbox"/> Unspecified		2011-07-22 16:17:04		

At the bottom of the page, there is a pagination control showing 'Page 1 of 1' and a 'Total: 2' indicator. The footer contains the 'AddPac' logo and copyright information: 'Copyright © AddPac 1999-2011 All Rights Reserved'.

# Card List (2/2)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### Card List

Display registered card list. Also, you can register a new card or modify/delete selected card(s).

Search List: All card  Search

	Serial Number	Extension	Username	Status	Description	Date Created	Modify	Delete
1	4000238	1008	Kwon hyojun	<input checked="" type="checkbox"/> Specified	Temporary cards are issued.	2011-07-08 15:59:03	<input type="button" value="Modify"/>	<input type="button" value="Delete"/>
2	123456789			<input type="checkbox"/> Unspecified		2011-07-22 16:17:04	<input type="button" value="Modify"/>	<input type="button" value="Delete"/>

#### Card

Read card serial number from access terminal or save by setting up a series of numbers.

Serial Number\*

Card Recognition

Description

User

Total: 2

**Card List**  
You may search RF card issue status (All Card / Serial Number / Extension) Issue/delete RF card by clicking 'Register a Card' button.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved



# Register a RF Card (1/2)

The image shows two overlapping screenshots of the AddPac Door Access Control System (DACS) web interface. The top screenshot shows the main navigation menu with the 'Card' dropdown menu open, highlighting the 'Register a Card' option. A mouse cursor is positioned over this option. The bottom screenshot shows the 'Card' registration page, which includes a form for entering card details. The form fields are: 'Serial Number\*' (with a dropdown menu set to 'Card recognition or enter directly'), 'Card Recognition' (with a dropdown menu set to 'Select card recognition terminal' and 'Read Card' and 'Write Card' buttons), 'Description' (text input), and 'User' (text input with a 'Reset' button). At the bottom of the form are 'Register' and 'Cancel' buttons. The interface also features a top navigation bar with 'Home', 'User and Terminal', 'Access Control', 'Card', and 'Log and Report' menus. A notification banner at the top right indicates 'Access control setting changed' and provides a link to 'here' to transmit settings to the terminal. The user is logged in as 'Administrator'. The footer of the interface displays 'AddPac Copyright © AddPac 1999-2011 All Rights Reserved'.

# Register a RF Card (2/2)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout Administrator

Home User and Terminal Access Control Card Log and Report

### Card

Read card serial number from access terminal or save by setting up a series of numbers. Setup to access into terminal by granting a card to user.

Serial Number\*  
Card Recognition  
Description  
User

Card recognition or enter directly

Select card recognition terminal

Read Card Write Card

Select card recognition terminal

- 2floor door terminal
- 3floor door terminal
- 5floor door terminal
- The main entrance door

Select User

Username	Extension	Department
Choi jnauk	1000	/3Floor(SM)
Kwon jonghui	1004	/
Oh hyounguk	1014	/3Floor(Framework)
Choi byunggu	1015	/3Floor(Framework)
Lee seonghyun	1016	/3Floor(Framework)
Hwang woosun	1111	/3Floor/
Han jiyoung	4099	/3Floor(SM)

**Register a Card**  
Register RF card which can be recognized in access terminal.

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# Event Log (1/2)

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

Event Log

Welcome to AddPac Technology Door Access Control System.

The door access control system(DACS) execute applicable features through...

**Import User and Terminal**

Import user and terminal list from IP-Next system to use Door Access Control System (DACS).

**Door Access Control System**  
Version 1.0.0

Access control setting changed  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

**Event Log**

Display various event log with search conditions (user, datetime, terminal registration..).

Duration : 2011-07-31 ~ 2011-08-30

User Extension Number :

Event Level : Error

Search Reset

Time	Level	User Extension	Event
------	-------	----------------	-------

Page 1 of 0

Event is not registered

AddPac Copyright © AddPac 1999-2011 All Rights Reserved

# Event Log (2/2)

**Door Access Control System**  
Version 1.0.0

① **Access control setting changed**  
To apply setting, click [here](#) to transmitting to terminal.

Help | Logout  
Administrator

Home User and Terminal Access Control Card Log and Report

### Event Log

Display various event log with search conditions (user, datetime, terminal registration..).

Duration : 2011-07-31 ~ 2011-08-30

User Extension Number :

Event Level : Error

Search Reset

- Error
- Critical
- Error
- Warning
- Notice
- Information
- Debug

Time	Level	User Extension	Event
------	-------	----------------	-------

Event is not registered

**Event Log**  
Search user information, access terminal status, and events which occurs from the access control system.

Duration  
User Extension Number  
Event Level  
\* Critical  
\* Error  
\* Warning  
\* Notice  
\* Information  
\* Debug

AddPac Copyright © AddPac 1999-2011 All Rights Reserved



# Thank you!

**AddPac Technology Co., Ltd.**  
Sales and Marketing

Phone +82.2.568.3848 (KOREA)

FAX +82.2.568.3847 (KOREA)

E-mail : [sales@addpac.com](mailto:sales@addpac.com)